



---

# NEM Event – Directions Report 22 November to 3 December 2020

---

**September 2021**

---

# Important notice

## PURPOSE

Where the Australian Energy Market Operator (AEMO) intervenes in the National Electricity Market (NEM) through the use of directions, AEMO must publish a report in accordance with National Electricity Rules (NER) clauses 4.8.9(f) and 3.13.6A(a). This report satisfies those NER obligations and is based on information available to AEMO at 18 June 2021.

Unless otherwise indicated, terms in this report have the same meanings as those defined in the NER.

All references to time in this report are based on Australian Eastern Standard Time (AEST).

## Disclaimer

AEMO has made every reasonable effort to ensure the quality of the information in this report but cannot guarantee its accuracy or completeness. Any views expressed in this report are those of AEMO unless otherwise stated and may be based on information given to AEMO by other persons.

Accordingly, to the maximum extent permitted by law, AEMO and its officers, employees and consultants involved in the preparation of this report:

- make no representation or warranty, express or implied, as to the currency, accuracy, reliability or completeness of the information in this document; and
- are not liable (whether by reason of negligence or otherwise) for any statements or representations in this document, or any omissions from it, or for any use or reliance on the information in it.

## ABBREVIATIONS

Abbreviation	Expanded name
AEMO	Australian Energy Market Operator
DI	Dispatch Interval
MN	Market Notice
NEM	National Electricity Market
NER	National Electricity Rules
PS	Power Station
SA	South Australia

# Contents

<b>1.</b>	<b>Summary</b>	<b>4</b>
<b>2.</b>	<b>Intervention assessment</b>	<b>5</b>
2.1	The need for intervention	5
2.2	Assessment of market response and latest time to intervene	6
<b>3.</b>	<b>Intervention process</b>	<b>6</b>
3.1	Adequacy of responses to AEMO inquiries	6
3.2	Participant ability to comply with the intervention	6
<b>4.</b>	<b>Dispatch and pricing outcomes</b>	<b>7</b>
4.1	Changes to dispatch outcomes due to the directions	7
4.2	Direction costs	7
<b>5.</b>	<b>Conclusions and further actions</b>	<b>7</b>

## Tables

Table 1	Summary of the South Australia directions between 22 November and 3 December 2020	4
Table 2	Participant offers	5
Table 3	Summary of latest time to intervene	6

# 1. Summary

To ensure adequate system strength for secure operation of the South Australian power system, certain combinations of synchronous generating units must be in service at all times<sup>1</sup>.

Clause 4.8.9 of the National Electricity Rules (NER) allows AEMO to intervene in the market by issuing directions or clause 4.8.9 instructions, if AEMO is satisfied that it is necessary to maintain or re-establish the power system to a secure, satisfactory, or reliable operating state. Section 116 of the National Electricity Law allows AEMO to issue directions to take certain action if AEMO considers that it is necessary to maintain power system security or for reasons of public safety.

Between 22 November and 3 December 2020, AEMO issued 11 directions across eight events to South Australian Market Participants to maintain power system security. These directions are summarised in Table 1.

**Table 1 Summary of the South Australia directions between 22 November and 3 December 2020**

Direction	Directed Participant	Event No.	Issue time	Direction instruction	Cancellation time
Pelican Point one Gas Turbine (GT) and Steam Turbine (ST) 18	Pelican Point Power Limited (ENGIE)	1	1700 hrs, 22 November 2020	Remain synchronised and follow dispatch targets from 0900 hrs, 23 November 2020	1700 hrs, 23 November 2020
Torrens Island PS B unit 2	AGL SA Generation Pty Ltd	1	2200 hrs, 22 November 2020	Remain synchronised and follow dispatch targets from 0030 hrs, 23 November 2020	1630 hrs, 23 November 2020
Torrens Island PS B unit 3	AGL SA Generation Pty Ltd	1	2200 hrs, 22 November 2020	Remain synchronised and follow dispatch targets from 0100 hrs, 23 November 2020	1700 hrs, 23 November 2020
Pelican Point one GT and ST 18	Pelican Point Power Limited (ENGIE)	2	1710 hrs, 23 November 2020	Remain synchronised and follow dispatch targets from 0900 hrs, 24 November 2020	1500 hrs, 24 November 2020
Pelican Point GT 12 and ST 18	Pelican Point Power Limited (ENGIE)	2	1945 hrs, 23 November 2020	Remain synchronised and follow dispatch targets from 0830 hrs, 24 November 2020	1600 hrs, 24 November 2020
Pelican Point one GT and ST 18	Pelican Point Power Limited (ENGIE)	3	1750 hrs, 24 November 2020	Remain synchronised and follow dispatch targets from 0830 hrs, 25 November 2020	1400 hrs, 25 November 2020
Pelican Point one GT and ST 18	Pelican Point Power Limited (ENGIE)	4	1600 hrs, 28 November 2020	Remain synchronised and follow dispatch targets from 0030 hrs, 29 November 2020	1500 hrs, 29 November 2020
Pelican Point one GT and ST 18	Pelican Point Power Limited (ENGIE)	5	1700 hrs, 29 November 2020	Remain synchronised and follow dispatch targets from 0800 hrs, 30 November 2020	1430 hrs, 30 November 2020
Pelican Point one GT and ST 18	Pelican Point Power Limited (ENGIE)	6	1730 hrs, 30 November 2020	Remain synchronised and follow dispatch targets from 0030 hrs, 1 December 2020	0400 hrs, 2 December 2020

<sup>1</sup> AEMO Transfer Limit Advice – System Strength, available at [https://aemo.com.au/-/media/files/electricity/nem/security\\_and\\_reliability/congestion-information/transfer-limit-advice-system-strength.pdf?la=en](https://aemo.com.au/-/media/files/electricity/nem/security_and_reliability/congestion-information/transfer-limit-advice-system-strength.pdf?la=en).

Direction	Directed Participant	Event No.	Issue time	Direction instruction	Cancellation time
Pelican Point one GT and ST 18	Pelican Point Power Limited (ENGIE)	7	1845 hrs, 1 December 2020	Remain synchronised and follow dispatch targets from 0800 hrs, 2 December 2020	1530 hrs, 2 December 2020
Pelican Point one GT and ST 18	Pelican Point Power Limited (ENGIE)	8	1800 hrs, 2 December 2020	Remain synchronised and follow dispatch targets from 0900 hrs, 3 December 2020	1000 hrs, 3 December 2020

## 2. Intervention assessment

### 2.1 The need for intervention

To ensure adequate system strength for secure operation of the South Australian power system, certain combinations of synchronous generating units must be in service at all times. If market conditions lead to market participants seeking to decommit synchronous generation AEMO is required to intervene to maintain the required level of synchronous units. The need for intervention, and options considered, were assessed against the set of viable plant combinations available at the time the directions were issued.

The requirement to intervene for the direction events in this report arose when the bids in Table 2 were submitted.

**Table 2 Participant offers**

Event No.	Unit	Offer date	Bid
1	Pelican Point PS	1323 hrs, 22 November 2020	Rebid to decommit from 0800 hrs, 23 November 2020 <sup>A</sup>
2	Pelican Point PS	1314 hrs, 23 November 2020	Rebid to decommit from 0900 hrs, 24 November 2020 <sup>B</sup>
3	Pelican Point PS	1326 hrs, 24 November 2020	Rebid to decommit from 0830 hrs, 25 November 2020 <sup>C</sup>
4	Pelican Point PS	1402 hrs, 28 November 2020	Rebid to decommit from 0030 hrs, 29 November 2020 <sup>D</sup>
5	Pelican Point PS	1347 hrs, 29 November 2020	Rebid to decommit from 0800 hrs, 30 November 2020 <sup>E</sup>
6	Pelican Point PS	1344 hrs, 30 November 2020	Rebid to decommit from 0030 hrs, 1 December 2020 <sup>F</sup>
7	Pelican Point PS	1343 hrs, 1 December 2020	Rebid to decommit from 0800 hrs, 2 December 2020 <sup>G</sup>
8	Pelican Point PS	1318 hrs, 2 December 2020	Rebid to decommit from 0900 hrs, 3 December 2020 <sup>G</sup>

A. Rebid reason: 1231~A~PRIMARY RESPONSE TO PREDISPATCH D+1~. Pelican Point PS was rebid one hour prior to direction effective time to stay in service commercially until 0900 hrs, 23 November 2020.

B. Rebid reason: 1230~A~PRIMARY RESPONSE TO PREDISPATCH D+1~

C. Rebid reason: 1259~F~REVISED TOLLING NOMINATION #2449-SL~

D. Rebid reason: 1402~F~REVISED TOLLING NOMINATION-SL~

E. Rebid reason: 1320~F~REVISED TOLLING NOMINATION #2463-SL~

F. Rebid reason: 1310~F~REVISED TOLLING NOMINATION #2464-SL~

G. Rebid reason: 1255~F~REVISED TOLLING NOMINATION #2476-SL~

H. Rebid reason: 1257~F~REVISED TOLLING NOMINATION #2469-SL~

## 2.2 Assessment of market response and latest time to intervene

Under NER clause 4.8.5A(a) and (c), AEMO must notify the market of any anticipated power system security or reliability issue, and the latest time for market response before AEMO would need to intervene.

AEMO contacted all participants who operate suitable generating units in South Australia to confirm their availability and the latest time to intervene. Those participants indicated that no market response would be provided but identified units that would be available if directed.

For each of the direction events, AEMO assessed the latest time to intervene taking account of the advised lead times. The latest times to intervene are listed in Table 3.

**Table 3 Summary of latest time to intervene**

Event No.	Latest time to respond	Market Notice
1	1700 hrs, 22 November 2020	MN 80235
2	1700 hrs, 23 November 2020	MN 80262
3	1800 hrs, 24 November 2020	MN 80295
4	1600 hrs, 28 November 2019	MN 80378
5	1700 hrs, 29 November 2020	MN 80495
6	1800 hrs, 30 November 2020	MN 80510
7	1900 hrs, 1 December 2020	MN 80559
8	1800 hrs, 2 December 2020	MN 80636

# 3. Intervention process

AEMO considers that it followed all applicable processes under NER clause 4.8 for the management of the directions between 22 November and 3 December 2020<sup>2</sup>.

## 3.1 Adequacy of responses to AEMO inquiries

NER clause 4.8.5A(d) permits AEMO to request information from Scheduled Network Service Providers, Scheduled Generators, Semi-Scheduled Generators, and Market Customers. AEMO is satisfied with the timeliness, adequacy, and effectiveness of all responses to its requests for information prior to issuing the directions between 22 November and 3 December 2020.

## 3.2 Participant ability to comply with the intervention

NER clause 4.8.9(d) requires that a Registered Participant must immediately notify AEMO of its inability to comply, or intention not to comply, with a direction or clause 4.8.9 instruction. AEMO is satisfied with all participants complying with the directions listed in Table 1.

<sup>2</sup> AEMO. Power system operating procedure SO\_OP 3707, "Procedures For Issue Of Directions And Clause 4.8.9 Instructions", 06 September 2019, available at [https://aemo.com.au/-/media/files/electricity/nem/security\\_and\\_reliability/power\\_system\\_ops/procedures/so\\_op\\_3707-procedures-for-issue-of-directions-and-clause-4-8-9-instructions.pdf?la=en](https://aemo.com.au/-/media/files/electricity/nem/security_and_reliability/power_system_ops/procedures/so_op_3707-procedures-for-issue-of-directions-and-clause-4-8-9-instructions.pdf?la=en).

# 4. Dispatch and pricing outcomes

## 4.1 Changes to dispatch outcomes due to the directions

The directions resulted in approximately 15,788 megawatt hours (MWh) of synchronous generation being directed into the market.

Intervention pricing did not apply for the event(s) in this report.

Under clause 3.8.1 of the NER, AEMO must operate a central dispatch process to balance power system supply and demand, using its reasonable endeavours to maintain power system security in accordance with NER Chapter 4 and the power system security standards. AEMO notes that in the absence of directions for system security, the central dispatch process would have produced an outcome which would have resulted in the operation of the power system in an unsecure state and would therefore have been an infeasible dispatch solution.

## 4.2 Direction costs

The compensation recovery costs for the direction between 22 November and 3 December 2020 were \$1,269,569. This amount includes two claims for additional compensation. Direction compensation recovery data can be found on the AEMO website<sup>3</sup>.

# 5. Conclusions and further actions

Between 22 November and 3 December 2020, AEMO issued 11 directions to South Australian Market Participants to maintain power system security, in response to a forecast lack of system strength in the region.

AEMO is satisfied that all applicable procedures and processes were followed in assessing the need for intervention, determining the latest time to intervene, enacting and managing the intervention and seeking market response from all generators capable of meeting the system strength requirements. The market was informed after each direction was issued.

AEMO is also satisfied with the timeliness and adequacy of participant responses and communication throughout.

---

<sup>3</sup> AEMO. Direction Compensation Recovery, available at <https://aemo.com.au/en/energy-systems/electricity/national-electricity-market-nem/data-nem/settlements-data/direction-compensation-recovery>